

LSM5

Internal: The LSM5 is configured with 120/277V input and a high-efficiency two stage charger providing precise float voltage control with low voltage disconnect protection. All components used in the circuitry are temperature compensated. Charger status is easily determined via a dual diagnostic LED display. Standard features include low voltage disconnect, AC lockout and brownout protection.

External: The LSM5 is constructed with a 20 gauge steel cabinet for lower wattages and 18 gauge steel for higher capacities. Terminal connectors allow for larger gauge wires to be connected for remote loads. The universal mounting pattern with key hole slots stamped into the back of the unit allows for direct mounting to various conduit boxes. Stamped conduit knockouts are supplied standard on all LSM5 units to optimize AC power source options.

Emergency Heads: The LSM5 is supplied standard with two top mounted heads with LED or incandescent lamps. LED lamp options include sealed beam LED LR style lamp heads, BTMR style heads with LED MR16 lamps, SR PAR18 style heads or TESSQ square LED lamp heads. Lamp heads can be mounted either on the top or on the sides of the unit allowing for up to four (4) heads to be mounted on the largest units (2 top, 2 side or 3 on top). The LR and SR lamp head styles are constructed of high impact thermoplastic in a standard white finish. BTMR, LR and SR head types feature a unique twist locking collar that securely holds the lens and facilitates quick and easy re-lamping.

Electrical:

BATTERY: The LSM5 is designed with a maintenance free, sealed valve regulated lead acid battery or optional Ni-Cd battery that provides a minimum emergency duration of 90 minutes (for the listed rating). Recharge time of the battery is 24 hours.


Mechanical: Remote lamp loads are connected to the emergency power supply with sturdy terminal connectors. These connectors allow for a large gauge of wire to be used increasing the flexibility of installation. The LSM5 is supplied standard in a durable white powder coat, baked finish. Black finish is optional and custom colors, please contact factory to specify.

Autotest: The Autotest system (optional) performs one 5 minute discharge test monthly. Every 6 months two 90 minute discharge tests are performed. This tests both full battery capacity and recharge capability, as required by the fire code. The information is communicated simply and intuitively to maintenance personnel via a single multi-color LED. The Autotest system also includes 0, 5, 10 or 20 minute time delay function to allow HID lighting to restrike. IRT one button press tests unit for 90 minutes per code.

Warranty: The LSM5 comes with a 3-year factory warranty. Lamps are not covered under the warranty. Deliberate damage, misuse, improper installation effectively cancel the warranty.



Dimensions (in,mm)



Unit Size	Steel (ga)	A	B	C
(6V 18-22W)	20	12 ^{1/4} " (311mm)	5" (127mm)	3" (76mm)
(6V 12V 36W)	20	10" (254mm)	9" (229mm)	3 1/4" (83mm)
(6V 42-90W) (12V 42-60W)	18	13 1/2" (343mm)	10 1/8" (257mm)	4 1/4" (108mm)
(12V 90W)	18	13" (330mm)	10 1/8" (257mm)	8 1/2" (216mm)

NOTE: Cabinet size may vary based on product configuration. Dimension D in drawing above will vary based on heads supplied.

Lamp Selection

	6V	12V
Incandescent ¹	7.2, 9W	9, 12, 18W
Quartz Halogen (Q) ²	12W	12, 20W
MR16 LED ³	5, 7W	2, 5, 7W
TESSQ ⁴	N/A	5, 9, 14, 30W
Sealed Beam LED ⁵	N/A	6W

NOTE 1: Available in LR lamp heads (ex: 2LR9W) and SR lamp heads (ex: 2SR18W)

NOTE 2: Available in LR lamp heads (ex: 2LR12Q) and SR lamp heads (2SR20Q)

NOTE 3: Available in SEA lamp heads (ex: 2SEA5WLED), SR lamp heads (ex: 2SR7WLED) and BTMR lamp heads (ex: 2BTMR2WLED)

NOTE 4: Nomenclature example: 2TESSQ9W

NOTE 5: Available in LR lamp heads (ex: 2LR6WLEDSB)



Job Name

Type

Part #

Notes

EXAMPLE: LSM5-618 2LR9W AT

NOTE 1: For nickel-cadmium battery, select NC from options and capacity from Ni-Cd column.

NOTE 2: Specify type of fire alarm signal: normally open, normally closed or 6, 12, 24VDC (specify voltage used).

NOTE 3: HHC (hand held controller for IBT) should be ordered separately (item code:476000021)

NOTE 4: Must specify input voltage and time delay (10 min standard)

NOTE 5: ENSURE BATTERY CAPACITY IS EQUAL TO OR HIGHER THAN

TOTAL LAMP WATTAGE

Model rating guide Pb-A (Capacity)

Model	Input Voltage	Wattage Rating 90 Minutes
LSM5 612	6	12
LSM5 618	6	18
LSM5 627	6	27
LSM5 636	6	36
LSM5 660	6	60
LSM5 1227	12	27
LSM5 1236	12	36
LSM5 1260	12	60

Model rating guide Ni-Cd (Capacity)

Model	Input Voltage	Wattage Rating 90 Minutes
LSM5 622	6	22
LSM5 642	6	42
LSM5 654	6	54
LSM5 690	6	90
LSM5 1242	12	42
LSM5 1290	12	90

* ENSURE MAX WATTS IS > TOTAL LAMP WATTAGE